

[0001] SPREAD SPECTRUM REMOTE UNIT

[0002] This patent is a continuation application of U.S. Patent Application No. 09/395,626, filed on September 14, 1999, which is a continuation application of U.S. Patent Application No. 08/871,479, filed on June 9, 1997, now U.S. Patent No. 5,974,039, issued October 26, 1999, which is a continuation application of U.S. Patent Application No. 08/628,012, filed on April 4, 1996, now U.S. Patent No. 5,663,956, issued September 2, 1997, which is a continuation application of U.S. Patent Application No. 08/311,773, filed September 23, 1994, now U.S. Patent No. 5,506,864, issued April 9, 1996, which is a continuation of U.S. Patent Application No. 08/178,016, filed February 23, 1994, now U.S. Patent No. 5,365,544, issued November 15, 1994, which was a file wrapper continuation application of U.S. Patent Application No. 08/006,851, filed January 21, 1993, now abandoned, which was a continuation-in-part application of U.S. Patent Application No. 07/622,235, filed December 5, 1990, now U.S. Patent No. 5,351,269, issued Sep. 27, 1994, and of U.S. Patent Application No. 07/626,109, filed December 14, 1990, now U.S. Patent No. 5,228,056, issued July 13, 1993.

[0003] BACKGROUND

[0004] This invention relates to spread-spectrum communications and more particularly to a system and method for locating within a cell, a remote unit communicating synchronously with a spread-spectrum-communications signal using a reference carrier signal supplied on a spread-spectrum channel by the transmitter.

[0005] DESCRIPTION OF THE RELEVANT ART

[0006] Referring to Figure 1, message data, $d(t)$, are processed by spread-spectrum modulator 51, using a message-chip-code signal, $g_1(t)$, to generate a spread-spectrum data

signal. The spread-spectrum data signal is processed by transmitter 52 using a carrier signal at a carrier frequency f_0 , and transmitted over communications channel 53.

[0007] At a receiver, a spread-spectrum demodulator 54 despreads the received spread-spectrum signal, and the message data are recovered by synchronous data demodulator 60 as received data. The synchronous data demodulator 60 uses a reference signal for synchronously demodulating the despread spread-spectrum signal. The square-law device 55, bandpass filter 56 and frequency divider 57 are well known in the art for generating a reference signal from a received modulated data signal. A Costas Loop or other reference signal generating circuit is adequate for this purpose.

[0008] In a fading channel, such as the ionosphere or any channel containing multipath, or more generally, any channel in which the received signal's amplitude fluctuates with time, synchronous demodulation is not practical since the phase of the incoming signal typically is not the same as the phase of the reference. In such cases differential phase shift keying (DPSK) is employed. With DPSK the received signal is delayed by one symbol and multiplied by the undelayed signal. If the resulting phase is less than $\pm 90^\circ$ a 0-bit is declared, otherwise a 1-bit is declared. Such a system is complex and suffers degradation of about 6 dB at error rates of 10^{-2} .

[0009] The prior art does not provide a system and method for synchronously communicating, using spread-spectrum modulation, with a base station and in combination locating a remote unit within the cell of a base station.

[0010] SUMMARY

[0011] A spread spectrum remote unit receives a spread spectrum signal. The spread spectrum signal includes a reference signal and a message signal. The message signal has message data. The reference signal is detected within the received combined spread spectrum signal. The message data of the message signal is recovered using the reference signal.

[0012] A spread spectrum remote unit produces a message signal having message data. A reference signal is produced. The reference signal is used in recovering the message data from a combined spread spectrum signal. The reference signal and the message signal is combined as a combined signal. The combined signal is transmitted as the combined spread spectrum signal.

[0013] BRIEF DESCRIPTION OF THE DRAWING(S)

[0014] The accompanying drawings, which are incorporated in and constitute a part of the specification, illustrate preferred embodiments of the invention, and together with the description serve to explain the principles of the invention.

[0015] Figure 1 is a prior art scheme for synchronously recovering message data;

[0016] Figure 2 shows a synchronous spread-spectrum system with a bit synchronizer, synchronized to a generic chip code generator according to the present invention;

[0017] Figure 3A shows a synchronous spread spectrum transmitter system for a plurality of message data;

[0018] Figure 3B shows a spread spectrum receiver using a synchronous detector for receiving a plurality of spread-spectrum processed signals;

[0019] Figure 3C shows a spread spectrum receiver using a nonsynchronous detector for receiving a plurality of spread-spectrum processed signals;

[0020] Figure 4 shows a synchronous spread-spectrum demodulating method;

[0021] Figure 5 is a block diagram of a base station for communicating synchronously with, and geolocating, a remote unit; and

[0022] Figure 6 is a block diagram of a remote unit for communicating with a base station and for geolocation.

[0023] DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT(S)

[0024] Reference is now made in detail to the present preferred embodiments of the invention, examples of which are illustrated in the accompanying drawings, wherein like reference numerals indicate like elements throughout the several views.

[0025] The spread-spectrum communications and geolocation system and method of the present invention is an extension of an invention disclosed in a U.S. patent application entitled, SYNCHRONOUS-SPREAD-SPECTRUM COMMUNICATIONS SYSTEM AND METHOD, by Donald L. Schilling, having U.S. Patent Application No. 07/626,109 and filing date of Dec. 14, 1990, now issued U.S. Patent No. 5,228,056. For completeness of disclosure, the following discussion includes the disclosure in the original patent application, and subsequently goes into a discussion for geolocation.

[0026] The spread spectrum signals of the present invention are designed to be "transparent" to other users, i.e., spread spectrum signals are designed to provide negligible interference to the communication of other existing users. The presence of a spread spectrum signal is difficult to determine. This characteristic is known as low probability of interception (LPI) and low probability of detection (LPD). The LPI and LPD features of spread spectrum allow transmission between users of a spread spectrum CDMA communications system without the existing users of the mobile cellular system experiencing significant interference. The present invention makes use of LPI and LPD with respect to predetermined channels in the mobile cellular system or in the fixed-service microwave system. By having the power level of each spread spectrum signal below the predetermined level, then the total power from all spread spectrum used within a cell does not interfere with mobile users in a mobile cellular system, or with microwave users in the fixed-service microwave system.

[0027] Spread spectrum is also "jam" or interference resistant. A spread spectrum receiver spreads the spectrum of the interfering signal. This reduces the interference from the interfering signal so that it does not noticeably degrade performance of the spread

spectrum system. This feature of interference reduction 10 makes spread spectrum useful for commercial communications, i.e., the spread spectrum waveforms can be overlaid on top of existing narrowband signals.

[0028] The present invention employs direct sequence spread spectrum, which uses a phase modulation technique. Direct sequence spread spectrum takes the power that is to be transmitted and spreads it over a very wide bandwidth so that the power per unit bandwidth (watts/hertz) is minimized. When this is accomplished, the transmitted spread spectrum power received by a mobile cellular user or a microwave user, having a relatively narrow bandwidth, is only a small fraction of the actual transmitted power.

[0029] In a fixed-service microwave system, by way of example, if a spread spectrum signal having a power of 10 milliwatts is spread over a fixed-service microwave bandwidth of 10 MHz and a microwave user employs a communication system having a channel bandwidth of only 2 MHz, then the effective interfering power due to one spread spectrum signal, in the narrow band communication system, is reduced by the factor of 10 MHz/2 MHz. For fifty concurrent users of spread spectrum, the power of the interfering signal due to spread spectrum is increased by fifty.

[0030] The feature of spread spectrum that results in interference reduction is that the spread spectrum receiver actually spreads the received energy of any interferer over the same wide bandwidth, 10 MHz in the present example, while compressing the bandwidth of the desired received signal to its original bandwidth. For example, if the original bandwidth of the desired message data is only 30 kHz, then the power of the interfering signal produced at a base station is reduced by 10 MHz/30 kHz.

[0031] Direct sequence spread spectrum achieves a spreading of the spectrum by modulating the original signal with a very wideband signal relative to the data bandwidth. This wideband signal is chosen to have two possible amplitudes, +1 and -1, and these amplitudes are switched, in a "pseudo-random" manner, periodically. Thus, at each equally spaced time interval, a decision is made as to whether the wideband modulating signal should

be +1 or -1. If a coin were tossed to make such a decision, the resulting sequence would be truly random. However, in such a case, the receiver would not know the sequence a priori and could not properly receive the transmission. Instead, a chip-code generator generates electronically an approximately random sequence, called a pseudo-random sequence, which is known a priori to the transmitter and receiver.

[0032] Code Division Multiple Access

[0033] Code division multiple access (CDMA) is a direct sequence spread spectrum system in which a number, at least two, of spread-spectrum signals communicate simultaneously, each operating over the same frequency band. In a CDMA system, each user is given a distinct chip code. This chip code identifies the user. For example, if a first user has a first chip code, $g_1(t)$, and a second user has a second chip code, $g_2(t)$, etc., then a receiver, desiring to listen to the first user, receives at its antenna all of the energy sent by all of the users. However, after despreading the first user's signal, the receiver outputs all the energy of the first user but only a small fraction of the energies sent by the second, third, etc., users.

[0034] CDMA is interference limited. That is, the number of users that can use the same spectrum and still have acceptable performance is determined by the total interference power that all of the users, taken as a whole, generate in the receiver. Unless one takes great care in power control, those CDMA transmitters which are close to the receiver cause overwhelming interference. This effect is known as the "near-far" problem. In a mobile environment the near-far problem could be the dominant effect. Controlling the power of each individual mobile remote user is possible so that the received power from each mobile remote user is the same. This technique is called "adaptive power control". See U.S. Patent No. 5,093,840, having issue date of March 3, 1992, entitled, ADAPTIVE POWER CONTROL FOR A SPREAD SPECTRUM SYSTEM AND METHOD, by Donald L. Schilling, which is incorporated herein by reference.

[0035] The spread spectrum communications system of the present invention is a code division multiple access (CDMA) system. Spread spectrum CDMA can significantly increase the use of spectrum. With CDMA, each user in a cell uses the same frequency band. However, each CDMA signal has a separate pseudo random code which enables a receiver to distinguish a desired signal from the remaining signals. Remote users in adjacent cells use the same frequency band and the same bandwidth, and therefore "interfere" with one another. A received signal may appear somewhat noisier as the number of users' signals received by a PCN base station increases.

[0036] Each unwanted user's signal generates some interfering power whose magnitude depends on the processing gain. Remote users in adjacent cells increase the expected interfering energy compared to remote users within a particular cell by about 50%, assuming that the remote users are uniformly distributed throughout the adjacent cells. Since the interference increase factor is not severe, frequency reuse is not employed.

[0037] Each spread spectrum cell can use a full 10 MHz band for transmission and a full 10 MHz band for reception. Hence, using a chip rate of five million chips per second and a coding data rate of 4800 bps results in approximately a processing gain of 1000 chips per bit. It is well known to those skilled in the art: that the maximum number of CDMA remote users that can concurrently use a frequency band is approximately equal to the processing gain.

[0038] Synchronous Spread Spectrum Communications

[0039] As illustratively shown in Figure 2, a spread spectrum code division multiple access (CDMA) communications system for use over a communications channel 110 is provided comprising generic means, message means, spreading means, summer means, transmitting means, generic-spread-spectrum-processing means, message-spread-spectrum-processing means, acquisition and tracking means, detection means and synchronous means. The generic means and message means are embodied as a transmitter-generic-chip-code generator 101 and transmitter-message-chip-code generator 102. The spreading means is

shown as an EXCLUSIVE-OR device 103, which may be an EXCLUSIVE-OR gate. Summer means is a combiner 105 and the transmitting means includes a transmitter which is embodied as a signal source 108 coupled to modulator 107. The transmitter-message-chip-code generator 102 is coupled to the EXCLUSIVE-OR device 103. The transmitter-generic-chip-code generator 101 is shown coupled to the transmitter-message-chip-code generator 102 and the source for message data. The EXCLUSIVE-OR device 103 and the transmitter-generic-chip-code generator 101 are coupled to the combiner 105. The modulator 107 is coupled between the combiner 105 and the communications channel 110.

[0040] At the receiver the generic-spread-spectrum-processing means is embodied as the receiver-generic-chip-code generator 121, the generic mixer 123 and the generic-bandpass filter 125. The generic mixer 123 is coupled between the receiver-generic-chip-code generator 121 and the generic-bandpass filter 125. The message-spread-spectrum-processing means is embodied as a receiver-message-chip-code generator 122, a message mixer 124 and, a message-bandpass filter 126. The message mixer 124 is coupled between the receiver-message-chip-code generator 122 and the message-bandpass filter 126. A power splitter 115 is coupled between the communications channel 110, and the generic mixer 123 and the message mixer 124.

[0041] The acquisition and tracking means is embodied as an acquisition and tracking circuit 131. The acquisition and tracking circuit 131 is coupled to an output of the generic-bandpass filter 125, and to the receiver-generic-chip-code generator 121. The receiver-message-chip-code generator 122 preferably is coupled to the receiver-generic-chip-code generator 121.

[0042] The detection means is embodied as a detector 139. The detector 139 is coupled to the message-bandpass filter 126 and the generic-bandpass filter 125. The detector 139 may be a nonsynchronous detector such as an envelope detector or square-law detector. Alternatively, the detector 139 may be a synchronous detector, which uses a recovered-carrier signal from the generic-bandpass filter 125.

[0043] The synchronous means includes bit means, a lowpass filter 128 and electronic switch 130. The bit means is embodied as a bit synchronizer 129. The lowpass filter 128 and electronic switch 130 are coupled to the bit synchronizer 129. The bit synchronizer 129, as shown in Figure 2, preferably is coupled to the receiver-generic-chip-code generator 121. Alternatively, the bit synchronizer 129 may be coupled to an output of the detector 139.

[0044] The transmitter-generic-chip-code generator 101 generates a generic-chip-code signal, $g_0(t)$, and the transmitter-message-chip-code generator 102 generates a message-chip-code signal, $g_1(t)$. Synchronous timing of the message data, $d_1(t)$, and the message-chip-code signal, in Figure 2, is provided by the generic-chip-code signal, although other sources can be used such as a common clock signal for synchronization. The EXCLUSIVE-OR device 103 generates a spread-spectrum signal by spread-spectrum processing message data with the message-chip-code signal. The spread-spectrum processing may be accomplished by modulo-2 adding the message data to the message-chip-code signal. The combiner 105 combines the generic-chip-code signal with the spread-spectrum-processed signal. The combined generic-chip-code signal and spread-spectrum-processed signal may be a multilevel signal, having the instantaneous voltage levels of the generic-chip-code signal and the spread-spectrum-processed signal.

[0045] The modulator 107, as part of the transmitter, modulates the combined generic-chip-code signal and spread-spectrum-processed signal by a carrier signal, $\cos \omega_c t$, at a carrier frequency, f_c . The modulated generic-chip-code signal and spread-spectrum processed signal are transmitted over the communications channel 110 as a code division multiple access (CDMA) signal, $x_c(t)$. Thus, the CDMA signal includes the generic-chip-code signal and the spread-spectrum-processed signal as if they were each modulated separately, and synchronously, on separate carrier signals having the same carrier frequency, f_c , and transmitted over the communications channel.

[0046] At a receiver, the generic-spread-spectrum-processing means recovers the carrier signal, $\cos \omega_c t$, from the CDMA signal, $x_c(t)$, and the message-spread-spectrum-

processing means despreads the CDMA signal, $x_c(t)$, as a modulated-data signal, $d_1(t)$. More particularly, referring to Figure 2, the CDMA signal received from the communications channel 110, is divided by power splitter 115. The receiver-generic-chip-code generator 121 generates a replica of the generic-chip-code signal, $g_0(t)$. The generic mixer 123 uses the replica of the generic-chip-code signal for despreading the CDMA signal, $x_c(t)$, from the power splitter 115, as a recovered-carrier signal. The spread-spectrum channel, of the CDMA signal having the generic-chip-code signal, $g_0(t) \cos \omega_c t$, generally does not include data so that despreading the CDMA signal produces the carrier signal, only. The generic-bandpass filter 125 filters the recovered-carrier signal at the carrier frequency, or equivalently, at an intermediate frequency. In comparison to the message-bandpass filter 126 which has a bandwidth sufficiently wide for filtering a modulated-data signal, the generic-bandpass filter 125 can have a very narrow bandwidth for filtering the recovered-carrier signal. The very narrow bandwidth of the generic-bandpass filter 125 assists in extracting the recovered-carrier signal from noise.

[0047] The acquisition and tracking circuit 131 acquires and tracks the recovered-carrier signal from an output of the generic-bandpass filter 125. The replica of the generic-chip-code signal from the receiver-generic-chip-code generator 121 is synchronized to the recovered-carrier signal via acquisition and tracking circuit 131.

[0048] The receiver-message-chip-code generator 122 generates a replica of the message-chip-code signal, $g_1(t)$. The replica of the message-chip-code signal, $g_1(t)$, is synchronized to the replica of the generic-chip-code signal, $g_0(t)$, from the receiver-generic-chip-code generator 121. Thus, the receiver-message-chip-code generator 122, via synchronization to the receiver-generic-chip-code generator 121, has the same synchronization as the transmitter-message-chip-code generator 102 via synchronization to the transmitter-generic-chip-code generator 101. Accordingly, the spread-spectrum communications channel having the generic-chip-code signal provides coherent spread-spectrum demodulation of the spread-spectrum channels with data.

[0049] The message mixer 124 uses the replica of the message-chip-code signal for despreading the CDMA signal from the power splitter 115, to generate a modulated-data signal, $d_1(t) \cos \omega_c t$. The modulated-data signal effectively is the message data modulated by the carrier signal. The message-bandpass filter 126 filters the modulated-data signal at the carrier frequency, or equivalently at an intermediate frequency (IF). Down converters, which convert the modulated-data signal to an IF, optionally may be used without altering the cooperative functions or teachings of the present invention.

[0050] The detector 139 demodulates the modulated-data signal as a detected signal. The detected signal is filtered through lowpass filter 128, sampled by electronic switch 130 and outputted as received data, $d_1(t)$. The received data, without errors, are identical to the message data. The lowpass filter 128 and electronic switch 130 operate in an "integrate and dump" function, respectively, under the control of the bit synchronizer 129.

[0051] The bit synchronizer 129 controls the integrating and dumping of lowpass filter 128 and electronic switch 130. The bit synchronizer 129 preferably derives synchronization using the replica of the generic-chip-code signal from the receiver-generic-chip-code generator 121 as illustrated in Figure 2. The bit synchronizer 129 also may derive synchronization from an output of the detector 139, as illustrated in Figure 1.

[0052] In a preferred embodiment, the bit synchronizer 129 receive the replica of the generic-chip-code signal, $g_0(t)$, from the receiver-generic-chip-code generator 121. The replica of the generic-chip-code signal, by way of example, may include a chip codeword having 8250 chips. Assuming that there are eleven bits per chip codeword, then there are 750 chips per bit of data. Since the replica of the generic-chip-code signal provides information to the bit synchronizer 129 as to where the chip codeword begins, the bit synchronizer 129 thereby knows the timing of the corresponding bits for synchronization.

[0053] The present invention further may include transmitting as the CDMA signal, a plurality of spread-spectrum-processed signals for handling a plurality of message data. In this case the invention includes a plurality of message means and a plurality of spreading

means. Referring to Figure 3A, the plurality of message means may be embodied as a plurality of transmitter-message-chip-code generators and the plurality of spreading means may be embodied as a plurality of EXCLUSIVE-OR gates. The plurality of transmitter-message-chip-code generators generates a plurality of message-chip-code signals. In Figure 3A, the plurality of transmitter-message-chip-code generators is shown as first transmitter-message-chip-code generator 102 generating first message-chip-code signal, $g_1(t)$, second transmitter-message-chip-code generator 172 generating second message-chip-code signal, $g_2(t)$, through N^{th} transmitter-message-chip-code generator 182 generating N^{th} message-chip-code signal, $g_N(t)$. The plurality of EXCLUSIVE-OR gates is shown as first EXCLUSIVE-OR gate 103, second EXCLUSIVE-OR gate 173, through N^{th} EXCLUSIVE-OR gate 183. The plurality of EXCLUSIVE-OR gates generates a plurality of spread-spectrum-processed signals by modulo-2 adding the plurality of message data $d_1(t)$, $d_2(t)$, \dots , $d_N(t)$ with the plurality of message-chip-code signals $g_1(t)$, $g_2(t)$, \dots , $g_N(t)$, respectively. More particularly, the first message data, $d_1(t)$, are modulo-2 added with the first message-chip-code signal, $g_1(t)$, the second message data, $d_2(t)$, are modulo-2 added with the second message-chip-code signal, $g_2(t)$, through the N^{th} message data, $d_N(t)$, which are modulo-2 added with the N^{th} message-chip-code signal, $g_N(t)$.

[0054] The transmitter-generic-chip-code generator 101 is coupled to the plurality of transmitter-message-chip-code generators and the source for the plurality of message data, $d_1(t)$, $d_2(t)$, \dots , $d_N(t)$. The generic-chip-code signal $g_0(t)$, in a preferred embodiment, provides synchronous timing for the plurality of message-chip-code signals $g_1(t)$, $g_2(t)$, \dots , $g_N(t)$, and the plurality of message data $d_1(t)$, $d_2(t)$, \dots , $d_N(t)$.

[0055] The combiner 105 combines the generic-chip-code signal and the plurality of spread-spectrum-processed signals, by linearly adding the generic-chip-code signal with the plurality of spread-spectrum-processed signals. The combined signal typically is a multilevel signal, which has the instantaneous voltage levels of the generic-chip-code signal and the plurality of spread-spectrum-processed signals.

[0056] The modulator 107, as part of the transmitter, modulates the combined generic-chip-code signal and the plurality of spread-spectrum-processed signals by a carrier signal, $\cos \omega_0 t$, at a carrier frequency, f_0 . The modulated generic-chip-code signal and the plurality of spread-spectrum processed signals are transmitted over the communications channel 110 as a CDMA signal, $x_c(t)$. The CDMA signal, $x_c(t)$ has the form:

$$x_c(t) = g_0(t) + \sum_1^N [g_i(t) + d_i(t)] \cos \omega_0 t$$

Thus, the CDMA signal includes the generic-chip-code signal and the plurality of spread-spectrum-processed signals as if they were each modulated separately, and synchronously, on separate carrier signals with the same carrier frequency, f_0 , and transmitted over the communications channel.

[0057] The present invention includes receiving a CDMA signal which has a plurality of spread-spectrum-processed signals. The receiver further includes a plurality of message-spread-spectrum processing means, a plurality of detection means and a plurality of synchronous means. The plurality of message-spread-spectrum-processing means, as shown in Figure 3B, may be embodied as a plurality of message-chip-code generators, a plurality of message mixers and a plurality of message-bandpass filters. A mixer is connected between a respective message-chip-code generator and message-bandpass filter. The plurality of message mixers is coupled to the power splitter 115. More particularly, the plurality of message-chip-code generators is shown embodied as first message-chip-code generator 122, second message-chip-code generator 172, through N^{th} message-chip-code generator 182. The plurality of message mixers is shown as first message mixer 124, second message mixer 174 through N^{th} message mixer 184. The plurality of message-bandpass

filters is shown as first message-bandpass filter 126, second message-bandpass filter 176, through N^{th} message-bandpass filter 186.

[0058] The plurality of detection means may be embodied as a plurality of synchronous detectors which is shown as first synchronous detector 127, second synchronous detector 177 through N^{th} synchronous detector 187. Each of the plurality of synchronous detectors are coupled to one of the plurality message-bandpass filters.

[0059] The plurality of synchronous means may include a bit synchronizer 129, a plurality of lowpass filters and a plurality of electronic switches. The plurality of lowpass filters is shown as first lowpass filter 128, second lowpass filter 178, through N^{th} lowpass filter 188. The plurality of electronic switches is shown as first electronic switch 130, second electronic switch 180 through N^{th} electronic switch 190. Each of the plurality of synchronous detectors is coupled to an output of the generic-bandpass filter 125. The recovered-carrier signal from the generic-bandpass filter 125 serves as the reference signal for synchronously demodulating each of the plurality of message-data signals by the plurality of synchronous detectors, as a plurality of received data, $d_1(t)$, $d_2(t)$, . . . , $d_N(t)$.

[0060] The detection means alternatively may be embodied as a plurality of nonsynchronous detectors, such as envelope detectors 139, 189, 199, as shown in Figure 3C. Typically, the nonsynchronous detectors do not require the recovered-carrier signal.

[0061] The bit synchronizer 129 derives timing from the replica of the generic-chip-code signal, $g_0(t)$, and controls the timing of the integrating and dumping functions of the plurality lowpass filters and the plurality of electronic switches.

[0062] With the use of the invention as embodied in Figure 3B, a generic-spread-spectrum channel, as part of the CDMA signal, provides the recovered-carrier signal, as discussed previously. The acquisition and tracking circuit 131 acquires and tracks the recovered-carrier signal from an output of the generic-bandpass filter 125. The replica of the generic-chip-code signal from the receiver-generic-chip-code generator 121 is synchronized to the recovered-carrier signal via acquisition and tracking circuit 131. The receiver-generic-

chip-code generator 121 generates a replica of the generic-chip-code signal, $g_0(t)$, which provides timing to bit synchronizer 129 and to the plurality of receiver-message-chip-code generators 122, 172, 182.

[0063] The present invention also includes a method for synchronously demodulating a CDMA signal. Message data are input to the spreading means. Referring to Figure 4, the method comprises the steps of generating 403 a generic-chip-code signal. The method further includes generating 405 message data synchronized to the generic-chip-code signal, and generating 407 a message-chip-code signal synchronized to the generic-chip-code signal. Message data are processed, using a spread-spectrum modulator, with the message-chip-code signal to generate a spread-spectrum-processed signal. The generic-chip-code signal is combined 409 with the spread-spectrum-processed signal. The method transmits 411 the combined generic-chip-code signal and spread-spectrum-processed signal on a carrier signal over the communications channel as a CDMA signal.

[0064] At a receiver, the method includes recovering 413 the carrier signal from the CDMA signal and despreading 415 the CDMA signal as a modulated-data signal. The recovered-carrier signal is used to synchronize the step of despreading the CDMA signal and to optionally synchronously demodulate 417 and output 419 the modulated-data signal as received data.

[0065] In use of system as set forth in Figure 3A, the transmitter-generic-chip-code generator 101 generates the generic-chip-code signal, $g_0(t)$. Message data are spread-spectrum processed by the EXCLUSIVE-OR device 103 with message-chip-code signal, $g_1(t)$, from transmitter-message-chip-code generator 102. The combiner 105 combines the generic-chip-code signal with the spread-spectrum-processed signal. The combined signal may be, for example, a multilevel signal, which is generated by linearly adding the voltage levels of the generic-chip-code signal and the spread-spectrum-processed signal, or by adding the voltage levels of the generic-chip-code signal with a plurality of spread-spectrum-processed signals. The transmitter transmits on a carrier signal having a carrier frequency,

f_o , the combined generic-chip-code signal and the plurality of spread-spectrum-processed signals. The CDMA signal is transmitted through the communications channel 110.

[0066] At the receiver, as shown in Figure 3B, the generic-spread-spectrum-processing means, embodied as the receiver-generic-chip-code generator 121, the generic mixer 123 and the generic-bandpass filter 125, cooperatively operate to recover the carrier signal from the CDMA signal. The message-spread-spectrum-processing means, embodied as the receiver-message-chip-code generator 122, the message mixer 124 and the message-bandpass filter 126, cooperatively despread the CDMA signal as the modulated-data signal. The receiver-message-chip-code generator 122 preferably is synchronized to the replica of the generic-chip-code signal from the receiver-generic-chip-code generator 121. A plurality of receiver-message-chip-code generators may be employed, synchronized to the replica of the generic-chip-code signal. The synchronous means, embodied as the synchronous detector 127 synchronized to the recovered-carrier signal, demodulates the modulated-data signal as received data.

[0067] The received data are integrated and dumped by lowpass filter 128 and electronic switch 130, under control of the bit synchronizer 129. The bit synchronizer 129 preferably uses the replica of the generic-chip-code signal for synchronizing the integrate and dump functions.

[0068] Spread Spectrum Geolocation

[0069] A spread spectrum code division multiple access (CDMA) communications and geolocation system and method for use over a communications channel is provided comprising at least one base station and a plurality of remote units. The remote units may be mobile or in a fixed, stationary location. Message data are communicated between the base stations and the remote units. Message data include, but are not limited to, digitized voice, computer data, facsimile data, video data, etc. The base station communicates base-message data to the plurality of remote units. A remote unit communicates remote-message data to the base station. Base-message data are defined herein to be message data originating

from a base station, and remote-message data are defined herein to be message data originating from a remote unit. The following discussion is of a preferred embodiment with the range between the base station and remote unit being determined at the base station. The roles of the base station and remote unit can be interchanged, as an equivalent to those skilled in the art, with the range being determined at the remote unit.

[0070] In the exemplary arrangement shown in Figure 5, a base station includes base-spreading means, base-generic means, base-combiner means, base-transmitter means, and base antenna. The term "base" is used as a prefix to indicate an element is located at the base station, or that a signal originates from a base station.

[0071] The base-spreading means spread-spectrum processes the base-message data, $d_1(t)$. The base-spreading means is embodied as a base-spread-spectrum modulator. The base-spread-spectrum in modulator is shown as a message-chip-code generator 502 and an EXCLUSIVE-OR gate 503. The EXCLUSIVE-OR gate 503 is coupled to the message-chip-code generator 502. The message-chip-code generator 502 uses a chip codeword for generating a chip-code sequence for spread-spectrum processing base-message data, $d_1(t)$. The chip-code sequence from message-chip-code generator 502 is spread-spectrum processed by modulo addition by EXCLUSIVE-OR gate 503. Many equivalent circuits can be used for the base-spread-spectrum modulator, including but not limited to, product devices for multiplying the chip-code sequence by the base-message data, matched filters and surface acoustic wave devices which have an impulse response matched to the chip-code sequence, as is well known to those skilled in the art.

[0072] The base-generic means generates a base-generic-chip-code signal. The term "generic" is used as a prefix to indicate that the generic-chip-code signal is an unmodulated, or low data rate, direct-sequence spread-spectrum signal, which can serve as a pilot channel. The pilot channel allows a user to acquire timing, and provides a phase reference for coherent demodulation. The base-generic means is embodied as a base-generic-chip-code generator 501. The base-generic-chip-code generator 501 generates a base-generic-chip-code signal,

using a chip codeword commonly shared with all remote units communicating with the base station. The message-chip-code generator 502 is coupled to the base-generic-chip-code generator 501, for deriving common timing. Alternatively, a common clock can be used for providing the timing signal to the message-chip-code generator 502 and the base-generic-chip-code generator 501.

[0073] The base-combiner means combines the base-generic-chip-code signal with the spread-spectrum-processed-base-message data, to generate a base-CDMA signal. The base-combiner means is embodied as a base combiner 505. The base combiner 505 is coupled to the base-generic-chip-code generator 501 and the EXCLUSIVE-OR gate 503. The base combiner 505 linearly adds the base-generic-chip-code signal with the spread-spectrum-processed-base-message data from EXCLUSIVE-OR gate 503. The resulting signal at the output of the base combiner 505 is a code division multiple access (CDMA) signal, denoted herein as the base-CDMA signal. Selected variations of nonlinear combining also may be used, so long as the resulting base-CDMA signal can have its channels detected at a spread-spectrum receiver.

[0074] The base-transmitter means transmits the base-CDMA signal from the base station to a remote unit. The base-transmitter means is embodied as a signal source 508 and product device 507. The product device 507 is coupled between the base combiner 505 and the signal source 508. The signal source 508 generates a first carrier signal at a first carrier frequency f_1 . The base-CDMA signal, from the output of the base combiner 505, is multiplied by the first carrier signal by product device 507. Other transmitting devices are well known in the art for putting a desired signal at a selected carrier frequency.

[0075] The base antenna 509 is coupled through an isolator 513 to the base-transmitter means. The base antenna 509 radiates the base-CDMA signal at the first carrier frequency.

[0076] As illustratively shown in Figure 6, a remote unit includes a remote antenna 511, remote-detection means, remote-spreading means, remote-combiner means, and remote-

transmitter means. Each remote unit also may include remote-generic means. The term "remote" is used as a prefix to indicate an element is located at a remote unit, or that a signal originates from the remote unit. The remote antenna 511 receives the base-CDMA signal radiated from the base station.

[0077] The remote-detection means is coupled to the remote antenna 511. The remote-detection means detects the base-generic-chip-code signal embedded in the base-CDMA signal. Using the detected-base-generic-chip-code signal, the remote-detection means recovers the base-message data communicated from the base station. A remote unit can retransmit the detected-base-generic-chip-code signal, or optionally, can have remote-generic means generate a different remote-generic-chip-code signal.

[0078] In Figure 6, the remote-detection means is embodied as a product device 536, bandpass filter 537, acquisition and tracking circuit 538, generic-chip-code generator 539, message-chip-code generator 541, product device 542, bandpass filter 543, data detector 544, lowpass filter 545, and bit synchronizer 540. As is well known in the art, other devices and circuits can be used for the same function, including but not limited to, matched filters, surface acoustic wave devices, etc. This circuit acquires and tracks the base-generic-chip-code signal embedded in the base-CDMA signal. The base-CDMA signal is received at remote antenna 511, and passes through isolator 534 and power splitter 535. The base-generic-chip-code signal is detected using product device 536, bandpass filter 537, acquisition and tracking circuit 538 and generic-chip-code generator 539. The function of this circuit is as described in the previous section. The detected-base-generic-chip-code signal is used to recover the base-messages data embedded in the base-CDMA signal, using message-chip-code generator 541, product device 542, bandpass filter 543, data detector 544, lowpass filter 545, and bit synchronizer 540. The data detector 544 may operate coherently or noncoherently. The detected base-message data is outputted as detected data, $d_{RI}(t)$.

[0079] If the base-generic-chip-code signal is to be combined as part of the remote-CDMA signal, then generic-chip-code generator 546 is not required, since the base-generic-

chip-code signal is available at the output of the generic-chip-code generator 539. If a remote-generic-chip-code signal, which is different from the base-generic-chip-code signal, is to be used, then the generic-chip-code generator 546 can be used for generating the remote-generic-chip-code signal. In the latter case, the remote-generic-chip-code signal is clocked or synchronized with the detected base-generic-chip-code signal. For purposes of discussion, the remote-generic-chip-code signal is considered to be sent from the remote unit to the base station, with the understanding that the remote-generic-chip-code signal can be identical to, or one and the same as, the detected base-generic-chip-code signal.

[0080] The remote-spreading means spread-spectrum processes remote-message data. The remote-spreading means is embodied as a remote-spread-spectrum modulator. The remote-spread-spectrum modulator is shown as a message-chip-code generator 548 and an EXCLUSIVE-OR gate 547. The EXCLUSIVE-OR gate 547 is coupled to the message-chip-code generator 548. The message-chip-code generator 548 uses a chip codeword for generating a chip-code sequence for spread-spectrum processing remote-message data, $d_2(t)$. The chip-code sequence from message-chip-code generator 548 is spread-spectrum processed by modulo addition by EXCLUSIVE-OR gate 547. Many equivalent circuits can be used for the remote-spreading means, including but not limited to, product devices for multiplying the chip-code sequence by the base-message data, matched filters and surface acoustic wave devices, as is well known to those skilled in the art.

[0081] The remote-generic-chip-code signal and the spread-spectrum-processed-remote-message data are combined by the remote-combiner means, as a remote-CDMA signal. The remote-combiner means is embodied as a remote-combiner 549. The remote combiner 549 is coupled to the EXCLUSIVE-OR gate 547, and the remote-generic-chip-code generator 546, or alternatively to the generic-chip-code generator 539. The remote combiner 549 linearly adds the remote-generic-chip-code signal with the spread-spectrum-processed-remote-message data from EXCLUSIVE-OR gate 547. The resulting signal at the output of the remote combiner 549 is a code division multiple access (CDMA) signal,

denoted herein as the remote-CDMA signal. Selected variations of nonlinear combining also may be used, so long as the resulting remote-CDMA signal can have its channels detected at a spread-spectrum receiver.

[0082] The remote unit also includes the remote-transmitter means for transmitting the remote-CDMA signal from the remote unit to the base station. The remote-transmitter means is embodied as a signal source 551 and product device 550. The product device 550 is coupled between the remote combiner 549 and the signal source 551. The signal source 551 generates a carrier signal at a second carrier frequency f_2 . The remote-CDMA signal, from the output of the remote combiner 549, is multiplied by the second carrier signal by product device 550. Other transmitting devices are well known in the art for putting a desired signal at a selected carrier frequency. The second carrier frequency may be the same as, or different from, the first carrier frequency.

[0083] The remote antenna 511 is coupled through an isolator 534 to the remote-transmitter means. The remote antenna 511 radiates the remote-CDMA signal at the second carrier frequency.

[0084] Each of the base stations further includes base-detection means and range means. The base-detection means is coupled to the base antenna 509 through isolator 513 and power splitter 515. The base detection means detects the remote-generic-chip-code signal embedded in the remote-CDMA signal. The base-detection means, as illustrated in Figure 5, may be embodied as a base detector which may includes a product device 523, bandpass filter 525, acquisition and tracking circuit 531, generic-chip-code generator 521, message-chip-code generator 522, product device 524, bandpass filter 526, data detector 527, lowpass filter 528, and bit synchronizer 529. As is well known in the art, the base detection means may be embodied with other devices and circuits which perform the same function, including but not limited to, matched filters, surface acoustic wave devices, etc. This circuit acquires and tracks the remote-generic-chip-code signal embedded in the remote-CDMA signal. The remote-CDMA signal is received at base antenna 509, and passes through

isolator 513 and power splitter 515. The remote-generic-chip-code signal is detected using product device 523, bandpass filter 525, acquisition and tracking circuit 531 and generic-chip-code generator 521. The function of this circuit is as previously described. The detected-remote-generic-chip-code signal is used to recover the remote-message data embedded in the remote-CDMA signal, using message-chip-code generator 522, product device 524, bandpass filter 526, data detector 527, lowpass filter 528, and bit synchronizer 529. The data detector 527 may operate coherently or noncoherently. The detected remote-message data is outputted as detected data, $d_{R2}(t)$. Thus, the base detector recovers, using the detected-remote-generic-chip-code signal, the remote message data communicated from the remote unit.

[0085] Using the detected-remote-generic-chip-code signal and the base-generic-chip-code signal, the range means determines a range delay between the remote unit and the base station. The range means is embodied as a range delay device 530, which can compare the timing between the base-generic-chip-code signal from the generic-chip-code generator 501, with the detected remote-generic-chip-code signal from the generic-chip-code generator 521.

[0086] The present invention may include further the steps of spread-spectrum processing the base-message data; generating a base-generic-chip-code signal; combining the base-generic-chip-code signal with the spread-spectrum-processed-base-message data, thereby generating a base-CDMA signal; transmitting the base-CDMA signal from the base station to the remote unit; detecting the base-generic-chip-code signal embedded in the base-CDMA signal; recovering, using the detected-base-generic-chip-code signal, the base-message data; spread-spectrum processing remote-message data; generating, using the detected-generic-chip-code signal and the spread-spectrum-processed-remote data, a remote-CDMA signal; transmitting the remote-CDMA signal from the remote unit to the base station; detecting the remote-generic-chip-code signal embedded in the remote-CDMA signal; recovering, using the detected-remote-generic-chip-code signal, the remote-message

data; and determining, using the detected-remote-generic-chip-code signal and the base-generic-chip-code signal, a range delay between the remote unit and the base station.

[0087] In use, the base station spread-spectrum processes the base-message data with a message-chip-code signal, and combines the spread-spectrum-processed-base-message data with a base-generic-chip-code signal. The combined signal is a base-CDMA signal which is transmitted over a communications channel to at least one remote unit.

[0088] The remote unit receives the base-CDMA signal, detects the base-generic-chip-code signal embedded in the base-CDMA signal, and uses the detected-base-generic-chip-code signal to recover the base-message data embedded in the base-CDMA signal.

[0089] The detected base-generic-chip-code signal is relayed as a remote-generic-chip-code signal, or is used to set the timing for a different remote-generic-chip-code signal, which is sent from the remote unit to the base station. The remote unit spread-spectrum processes the remote-message data with a remote-chip-code signal, and combines the spread-spectrum-processed-remote-message data with the remote-generic-chip-code signal as a remote-CDMA signal. The remote-CDMA signal is sent over the communications channel to the base station.

[0090] At the base station, the remote-generic-chip-code signal is detected from the remote-CDMA signal, and the detected remote-generic-chip-code signal is used to detect the remote-message data embedded in the remote-CDMA signal. Additionally, the detected remote-generic-chip-code signal is compared with the base-generic-chip-code signal in a range-delay circuit, to determine the range of the remote unit from the base station. Effectively, the range between the remote unit and the base station is a function of the timing between sending a sequence of the chip codeword which generated the base-generic-chip-code signal, and receiving the sequence generated by the chip codeword which generated the remote-generic-chip-code signal.

[0091] The concept of using a radio frequency (RF) signal to determine range is well known in the art. The RF signal is subject to a fixed rate of propagation, 3×10^8 meters/sec.

The RF signal leaves a transmitter some time before it reaches a receiver. A particular sequence of the base-generic-chip-code signal and remote-generic-chip-code signal are used as a mark in time. The difference in time of the sequence of the base-generic-chip-code signal as seen at the receiver of the remote unit, from that present at the transmitter of the base station, is related directly to distance between the base station and remote unit. Similarly, the difference in time of the sequence of the remote-generic-chip-code signal as seen at the receiver of the base station from that present at the transmitter of the remote unit, is related directly to distance between the remote unit and base station.

[0092] The use of the base-generic-chip-code signal and the remote-generic-chip-code signal is a common type of echo range measurement method that is used in radar systems. Many radar systems simply employ a pulse of RF energy and then wait for a return of a portion of the energy due to the pulse being reflected from objects. The radar marks time from the instant of pulse transmission until its return. The time required for the pulse to return is a function of the two-way range to the object. The range is easily determined from the signal propagation speed.

[0093] The spread-spectrum signals of the present invention are subject to the same distance/time relationship. The spread-spectrum signal of the present invention has an advantage in that its phase is easily resolvable. The basic resolution of a sequence of a base-chip-code signal or a remote-chip-code signal is one code chip. Thus, the higher the chip rate, the better the measurement capability. Thus, at a chip rate of 10 Mchips/sec, a basic range resolution is 10^{-7} seconds, or 30 meters.

[0094] Additional delays may be encountered in the circuitry of the remote unit. These delays can be compensated at the base station, when determining the distance between the base station and the remote unit.

[0095] It will be apparent to those skilled in the art that various modifications can be made to the synchronous spread-spectrum communications system and method of the instant invention without departing from the scope or spirit of the invention, and it is intended that

the present invention cover modifications and variations of the synchronous spread-spectrum communications system and method provided they come in the scope of the appended claims and their equivalents.

*

*

*

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211